

## Note on the Firmware Release for ATW-T5201/ATW-T5202

### Devices Intended for Update

Model	Update version	File name
ATW-T5201DE1	Ver 1.7.0	ATW-T5201-DE1-EG1- EF2_001.007.000.EXE
ATW-T5201EG1		
ATW-T5201EF2		
ATW-T5201GH1	Ver 1.4.0	ATW-T5201- GH1_001.004.000.EXE
ATW-T5201DE1J	Ver 1.8.0	ATW-T5201-DE1J-EG1J_ 001.008.000.EXE
ATW-T5201EG1J		
ATW-T5202DE1	Ver 1.7.0	ATW-T5202-DE1-EG1- EF2_001.007.000.EXE
ATW-T5202EG1		
ATW-T5202EF2		
ATW-T5202GH1	Ver 1.4.0	ATW-T5202- GH1_001.004.000.EXE
ATW-T5202DE1J	Ver 1.8.0	ATW-T5202-DE1J-EG1J_ 001.008.000.EXE
ATW-T5202EG1J		

Ver 1.7.0 (DE1/EG1/EF2) / 1.4.0 (GH1) / 1.8.0 (DE1J/EG1J)

### Improvements

- We have fixed a problem related to the RF POWER settings.
- We have fixed a problem related to the TEST TONE function.

### About Application for Update

- A dedicated application is used for updating the transmitter. The application can be used on a Windows PC.
- Transmitter firmware is updated via the IR sync function on an ATW-R5220 or ATW-R5220DAN receiver.

### Compatible OS

Windows 8.1 or higher

# About the Firmware Update

## Precautions

- Always download the latest firmware when executing a firmware update. Check our website ([www.audio-technica.com/world\\_map/](http://www.audio-technica.com/world_map/)) for the latest information on firmware.
- Read the following procedures carefully when executing an update.
- While updating, do not perform any functions on the receiver and transmitter.
- While updating, do not turn off the power or unplug the power cable from the receiver.
- While updating, do not disconnect the network cable connecting the receiver to the Windows PC.
- If the device being updated is not recognized, check the IP setting of the Windows PC connected to the transmitter.
- The application might not start up due to the firewall or security software of the PC being used. In this case, check the firewall settings and authorize communication with this application. For detailed information regarding the use of a Windows PC or security software, refer to the user manual of the transmitter being used.
- Depending on the operating system and security software being used, confirmation screens requesting communication authorization may be displayed during setup. If these appear, authorize the communication.
- Contact your local Audio-Technica dealer if the update fails and the receiver/transmitter does not start.

## Preparing


### Connect your Windows PC to the ATW-R5220

1. Before connecting the receiver to the Windows PC, ensure network settings of the Windows PC match the IP mode setting of the receiver.
  - When the receiver is set to "Auto", set the IP address to automatic acquisition. When the receiver is set to "Static", set the IP address to fixed.
  - The default setting of the receiver is "Auto".
2. Use a wired connection to connect your Windows PC to the receiver.
3. Turn on your Windows PC and the receiver.


## Updating

Make sure the transmitter being updated is powered OFF at this point.

1. Download the latest firmware from our website.
2. Launch the downloaded file as an administrator.
  - The Update Wizard starts.
3. Click "NEXT".




4. Select "ATW-T5201" or "ATW-T5202" and click "NEXT".
  - When you click the  button, the OLED display of the corresponding product blinks and you can identify the device you want to update.




# About the Firmware Update


5. The update starts.



6. When the screen below appears, click "OK".



7. Turn on the transmitter while pressing and holding the SET and SYNC buttons simultaneously.




8. Keep pressing and holding the SET and SYNC buttons for about 5 seconds.


- The transmitter starts up in BOOT MODE.

9. Position the IR SYNC windows of the receiver and transmitter so they face each other.

- Hold the transmitter in this position until communication is complete.




ATW-T5202



10. When the update is complete, click "CLOSE" to finish.

- To update another device, click "NEXT".



- If the update fails, update again following the display on the receiver.
- If the transmitter is turned on after a failed update, "NO APPLICATION FIRMWARE" will appear on the display. In this case, the transmitter will not work properly. Perform steps 7 and 8 to turn on the transmitter and update the firmware again.

# Notes on the Past Firmware Releases

---

## Ver 1.6.0 (DE1/EG1/EF2)

### Improvements

---

- We have fixed a problem related to the RF OFF function using the function button.

## Ver 1.5.0 (DE1/EG1/EF2)

### Additional Functions

---

- The transmitter now retains the "Mute" and "RF Off" settings of the function button when power is cycled.
- The transmitter now powers on to the last screen displayed before power was turned off.

## Ver 1.4.0 (DE1/EG1/EF2)

### Improvements

---

- We have fixed a minor bug related to the backup frequency function.

## Ver 1.3.0 (GH1)

### Improvements

---

- We have fixed a problem related to the RF OFF function using the function button.
- We have fixed a problem related to the frequency setting via IR SYNC.

## Ver 1.2.0 (GH1)

### Additional Functions

---

- The transmitter now retains the "Mute" and "RF Off" settings of the function button when power is cycled.
- The transmitter now powers on to the last screen displayed before power was turned off.

## Ver 1.1.0 (GH1)

### Improvements

---

- We have fixed a minor bug related to the backup frequency function.

## Ver 1.7.0 (DE1J/EG1J)

### Improvements

---

- We have fixed a problem related to the RF OFF function using the function button.

# Software License Agreement

## Software License Agreement of Audio-Technica Corporation

This Software License Agreement (hereinafter referred to as the "Agreement") is a legal agreement between you, the customer, and Audio-Technica Corporation ("Audio-Technica") with respect to the software downloaded from the website of Audio-Technica (hereinafter referred to as the "Software"). You shall, when downloading the Software from the Audio-Technica website, installing the downloaded Software, or using it, carefully read the following provisions without fail. You shall be considered to agree to this Agreement when you use the Software. You may not install and use the Software in the case where you do not agree to all the provisions of this Agreement.

### Article 1. License and Copyright etc.

- (1) Audio-Technica shall grant to you the right to use the program and data file consisting of the Software and the upgraded programs and data file thereof, which can be provided to you with certain conditions in the future (hereinafter referred to as the "Licensed Program") within the scope specified in this Agreement.
- (2) The Licensed Program is protected by the copyright and treaty concerning the copyright and other laws and treaties concerning the intellectual property right. The ownership, copyright, and any and all other intellectual property rights to and in the Licensed Program shall vest in Audio-Technica or Audio-Technica's licensor.
- (3) The right to and in the data generated by using the Licensed Program shall vest in you.

### Article 2. Scope of Use

The scope of your use of the Licensed Program shall be as stipulated below.

- (1) You may use the Licensed Program in your computer.
- (2) You may reproduce the Licensed Program only for the purpose of backing up the data input by you; provided, however, that the reproduction shall not be used simultaneously in any other computer, whether possessed by you or any third party, except when used to recover the backup data.

### Article 3. Restriction of Use

You shall, when using the Licensed Program, comply with the following matters.

- (1) You may transfer the Licensed Program to any other computer possessed by you; provided, however, that in such a case the Licensed Program shall be completely removed from the computer from which the Licensed Program is transferred.
- (2) You shall not distribute or transmit the Licensed Program.
- (3) You shall not lend, lease, or pledge collateral on the Licensed Program.
- (4) You shall neither reverse-engineer, decompile, disassemble, modify, or alter the Licensed Program nor make software derived from the Software.

### Article 4. Limitation of Warranty

- (1) Audio-Technica shall in no event warrant, explicitly or implicitly, the Licensed Program's merchantability, fitness for a particular purpose, or non-infringement of third-party rights. Furthermore, Audio-Technica shall in no event warrant that the Licensed Program operates properly and shall in no event warrant that any failure or defect in the Licensed Program can be modified.
- (2) Any and all information or advice provided by Audio-Technica, orally or in writing, etc., shall not be considered to provide a new warranty or expand the scope of the warranty specified in this article in any sense whatsoever.

### Article 5. Limitation of Liability

- (1) You shall be liable for any and all direct and indirect damages (such as loss of data, computer failure, cessation of business, and complaints from any third party) and risks arising out of the use of the Licensed Program.
- (2) Audio-Technica shall, in no event, be liable to you or any other third party for any direct, indirect, special, incidental or consequential loss or damage including but not limited to any loss of business values, suspension of business, loss or damage arising out of computer failure, or any other commercial loss or damage.

### Article 6. Assignment of Licensed Program

You may assign the right to use the Licensed Program to any third party; provided, however, that in this case you shall completely delete the Licensed Program from the recording media of your computer and shall not possess any reproduction of the Licensed Program, and the assignee shall agree to any and all provisions of this Agreement.

### Article 7. Cancellation and Termination of This Agreement

- (1) In the case where you violate any of the provisions of this Agreement, Audio-Technica may cancel this Agreement with immediate effect without demand.
- (2) In the case where this Agreement is canceled, you shall completely delete the Licensed Program from the recording media of your computer and destroy the reproduction of the Licensed Program.
- (3) Audio-Technica shall be exempt from any and all responsibilities for any damage, etc. which you or any third party suffer because it becomes impossible to use the Licensed Program as a result of the cancellation of this Agreement.

### Article 8. Governing Law and Miscellaneous Provisions

- (1) This Agreement shall be governed by the laws of Japan.
- (2) It is agreed that any dispute arising in relation to this Agreement or the Licensed Program shall be subject to the jurisdiction of the Tokyo District Court or Tokyo Summary Court in the first instance, depending on the amount sued for.

#### Audio-Technica Corporation

2-46-1 Nishi-naruse, Machida, Tokyo 194-8666, Japan  
www.audio-technica.com

©2022 Audio-Technica Corporation

Global Support Contact: www.at-globalsupport.com 232417150-02-04

ver.1 2019.03.15  
ver.4 2022.04.15